



All dimensions are in mm; tolerances according to ISO 2768 m-H

### Description

This fiber distribution unit is used for fiber management on top of the mast or at the base station. Brackets ensure an easy installation at a wall or mast (mast mounting requires additional mounting material).

### Fiber Termination

Capacity 12 fibers  
Adapter 6 x LC Duplex single mode adapters (preinstalled)

### Parts

Box	Polycarbonat	1 pce (UV resistant, RAL 7035)
Wall mounting brackets	Steel, zinc plated	2 pcs
Cable gland M40x1.5 mm	Plastic	1 pce
Cable gland M25x1.5 mm	Plastic	2 pcs
Insert 3x7mm, M25x1.5 mm	Rubber	2 pcs
LC-Duplex Adapters	Plastic	6 pcs
FO Adapter plate	Steel, powder coated	1 pce
Air valve M20	Plastic	1 pcs
Screw and washer mounting set	Stainless steel	4 pcs (M4x16mm)
Hinge	Plastic	1 pcs

### Cable entry

Distribution head 1 x M40x1,5 mm cable gland (preinstalled)  
Jumper cables 2 x M25x1,5 mm cable gland (preinstalled), each suitable for 3 individual jumpers (Ø 7 mm)

**FTTA Fiber Distribution Unit**  
6 duplex cables

**SLFDU004-06**

**Environmental data**

Temperature range                    -40 °C to +85 °C  
Degree of protection                IP66  
2002/95/EC (RoHS)                compliant

**Packing**

Standard                                1 pce in box  
Weight                                 tbd g / pce

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
S.Gleich	12.04.11	H.Schütt	12/04/11	100	11-0004	S.Gleich	12/04/11

Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de				Tel. : +49 8684 18-0 Fax. : +49 8684 18-499 Email : info@rosenberger.de			Page 2 / 2
--	--	--	--	---	--	--	---------------

RF\_35/06:10/1.0